



A.

Pool OR Spa



B.

Pool & Spa Combo

Control Your Pool AND Spa Combo

PE24065RC Kit Includes:

- PE20000 Load Center with 60 Amp Base
- PE653RC MultiWave Control System
- Water and Air Sensor with Mounting Hardware
- P4043ME Actuator Controller
- (2) PE24VA Valve Actuators
- Equipment Labels

PE20000RC Series Kits 60 Amp MultiWave Control System



- For a single pool or spa or a pool/spa combo
- Load center with four position 60 Amp breaker base
- Two knockouts for GFCIs and switches
- Controls 5 circuits
- Full thermostat control
- Operates single, two, and variable-speed pumps
- 24-hour scheduling capability for all connected equipment
- Type 3R indoor/outdoor 0.048" steel load center

Model #	Application	Actuator Control	Valve Actuators
A. PE20065RC	Pool or Spa	—	—
B. PE24065RC	Pool/Spa Combo	P4043ME	2 (PE24VA)

Each kit also includes (3) AA batteries and a flathead screwdriver.

Ratings:

Load Center Rating: 60 A, 120/240 VAC or 120/208 VAC single phase

Control Supply: 120/240 VAC, 50/60 Hz, 5 W max.

Circuit 1: 20 A Resistive (17 FLA, 80 LRA) 120, 240 VAC 50/60 Hz.

Circuits 2-5: 15 A Resistive (10 FLA, 60 LRA) 120, 240 VAC 50/60 Hz.

Load Center Dimensions: 16 1/2" (41.9 cm) H x 10 5/8" (27.6 cm) W x 4 1/4" (10.8 cm) D

Knockouts:

Bottom: (2) 1.09" ϕ through holes, (6) combination 1/2" – 3/4", (3) combination 3/4" – 1"

Left: (2) combination 1/2" – 3/4"

Back: (1) combination 3/4" – 1"

Right: (1) 1 3/4" x 2 3/4" for mounting switches or GFCI

Warranty: 2 year