

PE30000 Series 80 Amp Pool/Spa Control System with Type 3R Load Center



- 80 Amp 8-position breaker base
- Includes P1353ME 3-circuit mechanism and load center
- P1353ME controls single and two-speed filter pumps, cleaner/booster pumps, and pool/spa landscape lighting

	Model #	Mechanism	Switch	Transformer
E.	PE30000	Load Center only	—	—
	PE30000T3	Load Center only	—	300W
F.	PE35300	P1353ME	3-SPST	—

<p>Ratings: P1353ME Switch Ratings Each Circuit (SPST): Input Voltage: 120/240 VAC, 50/60 Hz. Contacts: 17 A Resistive 120/240 VAC, 5 A Tungsten 120/240 VAC, 17 FLA, 80 LRA 120/240 VAC Auxiliary Switch: 2 A, 24 VAC Load Center Dimensions: 22" (55.9 cm) H x 14 3/4" (37.5 cm) W x 4 1/4" (10.8 cm) D</p>	<p>Knockouts: Bottom: (1) 1.09"ø through hole, (6) 1/2" - 3/4", (2) 3/4" - 1" - 1 1/4", (4) 1/2" Left: (2) 1/2" - 3/4" Back: (4) 1/2" - 3/4", (2) 3/4" - 1" Right: (1) 1 3/4" x 2 3/4" for mounting switches or GFCI Warranty: 1 year</p>
--	--



E.



F.

PE40000 Series 125 Amp Pool/Spa Control System with Type 3R Load Center



- 125 Amp 8-position breaker base
- Includes P1353ME 3-circuit mechanism and load center
- P1353ME controls single and two-speed filter pumps, cleaner/booster pumps, and pool/spa landscape lighting

	Model #	Mechanism	Switch
G.	PE40000	Load Center only	—
H.	PE45300	P1353ME	3-SPST

<p>Ratings: P1353ME Switch Ratings Each Circuit (SPST): Input Voltage: 120/240 VAC, 50/60 Hz. Contacts: 17 A Resistive 120/240 VAC, 5 A Tungsten 120/240 VAC, 17 FLA, 80 LRA 120/240 VAC Auxiliary Switch: 2 A, 24 VAC Load Center Dimensions: 26" (66.3 cm) H x 18" (45.9 cm) W x 5 1/2" (14 cm) D</p>	<p>Knockouts: Bottom: (1) 1.09"ø through hole, (13) 1/2" - 3/4", (2) 3/4" - 1" - 1 1/4", Left: (1) 1/2" - 3/4", (2) 3/4" - 1" Back: (4) 1/2" - 3/4", (2) 3/4" - 1" Right: (1) 1 3/4" x 2 3/4" for mounting switches or GFCI Warranty: 1 year</p>
--	---



G.



H.

For further information on P1353ME mechanism, see page 120.

Wiring devices may be installed in this load center
(order (4) 21T156A standoffs for mounting). See page 154.