

Bridgeport Fittings Inc.


705 Lordship Blvd. Stratford, CT 06615

Phone: 203-377-5944 Fax: 203-381-3488

Push-EMT Grounding Bushings

Images





Dimension A in Inches: 1.09 Dimension B in Inches: 1.25 Dimension C in Inches: 1.06

Application

Bridgeport's Mighty-Bite Push-EMT Push on Grounding bushing is used to terminate service 1/2" EMT conduit. The integrated zinc die cast lug with dual ports is suitable for use with #14 - #4 wire and is provided for bonding EMT. Captive nylon 105 degree C insulator prevents damage to wire insulation. Easy installation, simply push onto conduit.

Product Information

Material: Zinc Die Cast

Certifications & Codes:

Federal Specification A-A-50553

Number:

NEMA Standard: FB-1

 UL File Number:
 cETLus Listed

 UL Standard:
 UL-514B

 UNSPSC:
 39121312

 Patent Number:
 D749,047;

 9,257,795

Catalog ID: 381-MB

UPC Number: 78174723381

Description: Mighty-Bite® Push-EMT™ Push on Grounding

Bushing, 1/2" Trade Size. Patented

Application: Bridgeport's Mighty-Bite Push-EMT Push on Grounding bushing is used to terminate service 1/2" EMT conduit. The integrated zinc die cast lug with dual ports is suitable for use with #14 - #4 wire and is provided for bonding EMT. Captive nylon 105 degree C insulator prevents damage to wire insulation. Easy installation, simply push onto conduit.

Trade Size: 1/2"

Std Pkg Qty: 250

Unit Qty: 25